



BEAMZ
MADE
EAZY

150.435 V1.0

COBRA WASH100
QUICK START GUIDE

CONTROL MENU

MENU		DESCRIPTION	
ADDR	A001-A512		DMX address
SET	nodE	dnh	DMX mode
		Ato 1	Auto running mode 1
		Ato 2	Auto running mode 2
		Son	Sound control mode
	Plnt	oFF	Pan forward move
		on	Pan reverse move
	tlnt	oFF	Tilt forward move
on		Tilt reverse move	
REST			Reset
CHND	CH19		DMX channel
CAL	PA S	C000-C255	Pan zero calibration
	PA E	C000-C255	Pan position calibration
	ti S	C000-C255	Tilt zero calibration
	ti E	C000-C255	Tilt position calibration
	SEnS	C000-C100	Sound sensitive

DMX CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	PAN	000-255	0-540 degree move
2	PAN FINE	000-255	16bit adjust
3	TILT	000-255	0-205 degree move
4	TILT FINE	000-255	16bit adjust
5	DIMMER	000-255	0-100% linear dimmer from dark to brighter
6	STROBE	000-003	OFF
		004-103	Synchronous Strobe from slow to fast
		104-107	ON
		108-207	Divide Strobe from slow to fast
		208-212	ON
		213-251	Random strobe from fast to slow
		252-255	ON
		7	WARM WHITE
8	COLD WHITE	000-255	Cold White linear dimmer from dark to brighter
9	COLOR TEMPERATURE	000-009	No Function
		010-255	Cold White to Warm White
10	HALO DIMMER	000-255	0-100% linear dimmer from dark to brighter
11	HALO STROBE	000-004	No Function
		005-250	Synchronous strobe from slow to fast
		251-255	No Function
12	HALO RED	000-255	Red linear dimmer from dark to brighter
13	HALO GREEN	000-255	Green linear dimmer from dark to brighter
14	HALO BLUE	000-255	Blue linear dimmer from dark to brighter
15	HALO COLOR	000-085	Red linear dimmer from brighter to dark, meanwhile, Green linear dimmer from dark to brighter
		086-170	Green linear dimmer from brighter to dark, meanwhile, Blue linear dimmer from dark to brighter
		171-255	Blue linear dimmer from brighter to dark, meanwhile, Red linear dimmer from dark to brighter
16	HALO EFFECT	000-004	No Function
		005-255	Halo Effects(Every 5 Values one effect)
17	HALO EFFECT SPEED	000-127	Clockwise water-flow effect from slow to fast
		128-255	Counterclockwise water-flow effect from slow to fast
18	PT SPEED	000-255	Speed from fast to slow
19	RESET	000-249	No Function
		250-255	All reset after 5s



BEAMZ

**YOUR FUTURE
YOUR SKILLS
YOUR PLATFORM
YOUR PARTY
YOUR EVENT**



is a leading developer of lighting products, including intelligent DMX moving heads, wireless battery operated DMX effects, static washes, sound-activated club effects, strobes & blacklights, LED lighting, fog and special effects machines, lasers and indoor and outdoor architectural lighting, as well as lighting controllers and protective bags.

