



**BEAMZ**  
**MADE**  
**EAZY**

150.692 V2.2

**STARCOLOR 360**

**QUICK **START** GUIDE**

# CONTROL MENU

MENU		DESCRIPTION	
<b>STATIC COLOR</b>	Red	RED 0-100%	
	Green	GREEN 0-100%	
	Blue	BLUE 0-100%	
	Amber	AMBER 0-100%	
	Strobe	STROBE 0-20HZ	
<b>AUTO</b>	Aut. (1-10)	SELECT AUTO PROGRAMM	
	Pro. (1-10)	SELECT PROGRAMM	
<b>RUN</b>	DMX	DMX MODUS	
	Slave	MASTER SLAVE MODUS	
<b>DMX ADDRESS</b>	Addr (1-512)	SELECT START ADDRESS	
<b>PERSONALITY</b>	Stage	12 CHANNEL MODE	
	Arc.1	3 CHANNEL MODE	
	AR1. D	4 CHANNEL MODE	
	Arc. 2	5 CHANNEL MODE	
	Ar2. D	6 CHANNEL MODE	
	Ar2. S	7 CHANNEL MODE	
	HSV	3 CHANNEL MODE	
	<b>ID ADDRESS</b>	Addr (01-66)	SET ID ADDRESS
<b>EDIT</b>	Pro01 – Sc01	SET ID ADDRESS	
	Pro02 – Sc02		
	Pro03 – Sc03		
	Pro04 – Sc04		
	Pro05 – Sc05		
	Pro06 – Sc06		
	Pro07 – Sc07		
	Pro08 – Sc08		
	Pro09 – Sc09		
	Pro10 – Sc10		
	<b>SET</b>	UPLD	PASSWORD: ****
Rest		PASSWORD: ****	
ID		ON	
		OFF	
RGBW		ON	
		OFF	
DIM		OFF	
		DIM 1	
		DIM 2	
		DIM 3	
		DIM 4	
<b>CAL1 WHITE</b>		WT01	RED (0-255)
		WT02	GREEN (0-255)
		WT03	BLUE (0-255)
	WT04	AMBER (0-255)	
	WT05		
	WT06		
	WT07		
	WT08		
	WT09		
	WT10		
	WT11		
<b>CAL2 PARAMETER</b>	RGBW	RED (0-255)	
		GREEN (0-255)	
		BLUE (0-255)	
<b>KEY LOCK</b>	On		
	OFF		

## DMX CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	DIMMER	000-255	Master dimmer 0-100%
2	RED	000-255	Dimmer 0-100%
3	GREEN	000-255	Dimmer 0-100%
4	BLUE	000-255	Dimmer 0-100%
5	WHITE	000-255	Dimmer 0-100%
6	AMBER	000-255	Dimmer 0-100%
7	COLOUR CHANGE	000-010	No function
		011-020	Red 100%, Green 100%, Blue 0%, White 0%, Amber 0%
		021-030	Intensity red (100% to 0% fade-in; if channel 8=0, no change), Green 100%, Blue 0%, White 0%, Amber 0%
		031-040	Red 0%, Green 100%, Blue 100%, White 0%, Amber 0%
		041-050	Red 0%, Intensity green (100% to 0% fade-in; if channel 8=0, no change), Blue 0%, White 0%, Amber 0%
		051-060	Red 0%, Green 0%, Blue 100%, White 100%, Amber 0%
		061-070	Red 0%, Green 0%, intensity blue (0% to 100% fade-in; if channel 8=0, no change), White 0%, Amber 0%
		071-080	Red 0%, Green 0%, Blue 0%, White 100%, Amber 100%
		081-090	Red 0%, Green 0%, Blue 0% intensity white (0% to 100% fade-in; if channel 8=0, no change), Amber 100%
		091-100	Colour transitions, speed is controlled via channel 8
		101-110	Colour transitions, speed is controlled via channel 8
		111-120	Colour transitions, speed is controlled via channel 8
		121-130	Colour transitions, speed is controlled via channel 8
		131-140	Colour transitions, speed is controlled via channel 8
		141-150	Colour transitions, speed is controlled via channel 8
		151-160	Colour transitions, speed is controlled via channel 8
		161-170	Colour transitions, speed is controlled via channel 8
		171-180	Colour transitions, speed is controlled via channel 8
		181-190	Colour transitions, speed is controlled via channel 8
		191-200	All LED
		201-205	White 1
		206-210	White 2
		211-215	White 3
		216-220	White 4
		221-225	White 5
226-230	White 6		
231-235	White 7		
236-240	White 8		
241-245	White 9		
246-250	White 10		
251-255	White 11		
8	STROBE	000-015	No function
		016-255	Strobe
9	AUTO PROGRAM	000-009	No function
		010-019	Auto program 1, speed is controlled via channel 10
		020-029	Auto program 2, speed is controlled via channel 10
		030-039	Auto program 3, speed is controlled via channel 10
		040-049	Auto program 4, speed is controlled via channel 10
		050-059	Auto program 5, speed is controlled via channel 10
		060-069	Auto program 6, speed is controlled via channel 10

		070-079	Auto program 7, speed is controlled via channel 10
		080-089	Auto program 8, speed is controlled via channel 10
		090-099	Auto program 9, speed is controlled via channel 10
		100-109	Auto program 10, speed is controlled via channel 10
		110-255	No function
10	SPEED	000-255	Speed
11	DIMMER SPEED	000-049	Dimmer function is off
		050-099	Dimmer speed 1
		100-149	Dimmer speed 2
		150-199	Dimmer speed 3
		200-255	Dimmer speed 4
12	ID ADDRESS	000-255	Select ID address see below table.

## ID ADDRESS

VALUE	DESCRIPTION	VALUE	DESCRIPTION
000-009	All ID's	223	ID 34
010-019	ID 1	224	ID 35
020-029	ID 2	225	ID 36
030-039	ID 3	226	ID 37
040-049	ID 4	227	ID 38
050-059	ID 5	228	ID 39
060-069	ID 6	229	ID 40
070-079	ID 7	230	ID 41
080-089	ID 8	231	ID 42
090-099	ID 9	232	ID 43
100-109	ID 10	233	ID 44
110-119	ID 11	234	ID 45
120-129	ID 12	235	ID 46
130-139	ID 13	236	ID 47
140-149	ID 14	237	ID 48
150-159	ID 15	238	ID 49
160-169	ID 16	239	ID 50
170-179	ID 17	240	ID 51
180-189	ID 18	241	ID 52
190-199	ID 19	242	ID 53
200-209	ID 20	243	ID 54
210	ID 21	244	ID 55
211	ID 22	245	ID 56
212	ID 23	246	ID 57
213	ID 24	247	ID 58
214	ID 25	248	ID 59
215	ID 26	249	ID 60
216	ID 27	250	ID 61
217	ID 28	251	ID 62
218	ID 29	252	ID 63
219	ID 30	253	ID 64
220	ID 31	254	ID 65
221	ID 32	255	ID 66
222	ID 33		

### ARC1 3 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	Red	000-255	Dimmer 0-100%
2	Green	000-255	Dimmer 0-100%
3	Blue	000-255	Dimmer 0-100%

### ARC1D 4 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	Dimmer	000-255	Master dimmer 0-100%
2	Red	000-255	Dimmer 0-100%
3	Green	000-255	Dimmer 0-100%
4	Blue	000-255	Dimmer 0-100%

### ARC2 4 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	Red	000-255	Dimmer 0-100%
2	Green	000-255	Dimmer 0-100%
3	Blue	000-255	Dimmer 0-100%
4	Amber	000-255	Dimmer 0-100%

### ARC2D 5 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	Dimmer	000-255	Master dimmer 0-100%
2	Red	000-255	Dimmer 0-100%
3	Green	000-255	Dimmer 0-100%
4	Blue	000-255	Dimmer 0-100%
5	Amber	000-255	Dimmer 0-100%

### ARC2S 6 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	Dimmer	000-255	Master dimmer 0-100%
2	Red	000-255	Dimmer 0-100%
3	Green	000-255	Dimmer 0-100%
4	Blue	000-255	Dimmer 0-100%
5	White	000-255	Dimmer 0-100%
6	Amber	000-255	Dimmer 0-100%

### ARC2S 7 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	Dimmer	000-255	Master dimmer 0-100%
2	Red	000-255	Dimmer 0-100%
3	Green	000-255	Dimmer 0-100%
4	Blue	000-255	Dimmer 0-100%
5	White	000-255	Dimmer 0-100%
6	Amber	000-255	Dimmer 0-100%
7	Strobe	000-255	0-20Hz

### HSU 3 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	Hue	000-255	0-100%
2	Saturation	000-255	0-100%
3	Dimmer	000-255	0-100%



A series of horizontal dotted lines spanning the width of the page, intended for handwriting practice.



A series of horizontal dotted lines for writing, spanning the width of the page.



# BEAMZ

**YOUR FUTURE**  
**YOUR SKILLS**  
**YOUR PLATFORM**  
**YOUR PARTY**  
**YOUR EVENT**



offers a wide range of high performance lighting equipment and related accessories for the rental, entertainment and architectural lighting markets. BeamZ Pro stands for performance, innovation and value pricing!

