



BEAMZ
MADE
EAZY

150.456 V1.0

SB220IP

QUICK START GUIDE

CONTROL MENU

MENU		DESCRIPTION
A001	001-512	DMX address setting
XCH	1Ch	1 channel mode
	3Ch	3 channel mode
	4Ch	4 channel mode
	8Ch	8 channel mode
CC.60	000-099	Jump mode from slow to fast
CP.60	000-099	Fade mode from slow to fast
DE.60	000-099	Pulse mode from slow to fast
R.000	000-099	Dimming head 1 warm white
G.000	000-099	Dimming head 1 amber
B.000	000-099	Dimming head 2 warm white
U.000	000-099	Dimming head 2 amber
ON	ON	Enable display
	OFF	Disable display if no operation
ATXX	Atxx	Head 1 temperature
	Btxx	Head 2 temperature

DMX CHANNELS

1 CHANNEL

CHANNEL	VALUE	DESCRIPTION
1	000-255	Dimming all LEDs tungsten function

3 CHANNEL

CHANNEL	VALUE	DESCRIPTION
1	000-255	Master dimming
2	000-255	Dimming head 1 tungsten function
3	000-255	Dimming head 2 tungsten function

4 CHANNEL

CHANNEL	VALUE	DESCRIPTION
1	000-255	Dimming head 1 warm white
2	000-255	Dimming head 1 amber
3	000-255	Dimming head 2 warm white
4	000-255	Dimming head 2 amber

8 CHANNEL

CHANNEL	VALUE	DESCRIPTION
1	000-255	Master dimmer
2	000-255	Dimming head 1 warm white
3	000-255	Dimming head 1 amber
4	000-255	Dimming head 2 warm white
5	000-255	Dimming head 2 amber
6	000-004	No function
	005-255	Strobe from slow to fast
	000-50	No Function
7	051-100	Jump mode from slow to fast
	101-150	Fade mode from slow to fast
	151-255	Pulse mode from slow to fast
8	000-255	If CH7=0-50, speed for dimming
		If CH7=51-255, speed for macro from slow to fast



BEAMZ

YOUR FUTURE
YOUR SKILLS
YOUR PLATFORM
YOUR PARTY
YOUR EVENT



offers a wide range of high performance lighting equipment and related accessories for the rental, entertainment and architectural lighting markets. BeamZ Pro stands for performance, innovation and value pricing!

