



BEAMZ
MADE
EAZY

150.708 V1

LCB246

QUICK START GUIDE

CONTROL MENU

MENU		DESCRIPTION
ADDR	A001-Axxx	DMX address setting
CHND	8Ch	Select DMX channel work mode
	11Ch	
	20Ch	
	38Ch	
	74Ch	
SLND	NASt	Master slave mode
	SL 1	
	SL 2	
SOUN	So 0 - 16	Select sound program
	SE 99-0	Adjust sound program sensitivity
AUTO	Au 0 - 16	Select automatic program
	SP 0 - 9	Adjust automatic program speed
COLO	Co 1 - 15	Select colour chase
NANU	rEd	Manual colour setting
	GrEE	
	bluE	
	Uht	
	ANbE	
	Uu	
DISP	DSIP	Display inverse
VER	vXX	Software version

COLOUR CHASE TABLE

VALUE	DESCRIPTION
000-007	No function
008-022	Colour chase 1
023-037	Colour chase 2
038-052	Colour chase 3
053-067	Colour chase 4
068-082	Colour chase 5
083-097	Colour chase 6
098-112	Colour chase 7
113-127	Colour chase 8
128-142	Colour chase 9
143-157	Colour chase 10
158-172	Colour chase 11
173-187	Colour chase 12
188-202	Colour chase 13
203-217	Colour chase 14
218-232	Colour chase 15
233-247	Colour chase 16
248-255	Sound active

DMX CHANNELS

8 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	Colour	000-255	Red 0-100%
2		000-255	Green 0-100%
3		000-255	Blue 0-100%
4		000-255	White 0-100%
5		000-255	Amber 0-100%
6		000-255	UV 0-100%
7	Colour Macro	000-255	See "Colour chase table"
8	Speed	000-255	Chase speed slow to fast

11 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	Dimmer	000-255	Dimmer 0-100%
2	Strobe	000-255	Strobe, slow to fast
3	Colour	000-255	Red 0-100%
4		000-255	Green 0-100%
5		000-255	Blue 0-100%
6		000-255	White 0-100%
7		000-255	Amber 0-100%
8		000-255	UV 0-100%
9	Program	000-255	Auto program
10	Colour Macro	000-255	See "Colour chase table"
11	Speed	000-255	Chase speed slow to fast

20 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	Section 1 Dimmer	000-255	Dimmer 0-100%
2	Section 1 Strobe	000-255	Strobe, slow to fast
3	Section 1 Colour	000-255	Red 0-100%
4		000-255	Green 0-100%
5		000-255	Blue 0-100%
6		000-255	White 0-100%
7		000-255	Amber 0-100%
8		000-255	UV 0-100%
9	Section 1 Program	000-255	Auto program
10	Section 2 Dimmer	000-255	Dimmer 0-100%
11	Section 2 Strobe	000-255	Strobe, slow to fast
12	Section 2 Colour	000-255	Red 0-100%
13		000-255	Green 0-100%
14		000-255	Blue 0-100%
15		000-255	White 0-100%
16		000-255	Amber 0-100%
17		000-255	UV 0-100%
18	Section 2 Program	000-255	Auto program
19	Colour Macro	000-255	See "Colour chase table"
20	Speed	000-255	Chase speed slow to fast



BEAMZ

YOUR FUTURE
YOUR SKILLS
YOUR PLATFORM
YOUR PARTY
YOUR EVENT



is a leading developer of lighting products, including intelligent DMX moving heads, wireless battery operated DMX effects, static washes, sound-activated club effects, strobes & blacklights, LED lighting, fog and special effects machines, lasers and indoor and outdoor architectural lighting, as well as lighting controllers and protective bags.

